Atmel Studio 7 – Grundinstallation

- 1. *Atmel Studio 7* aus dem *Microchip* Download-Archiv herunterladen (ca. 900MB): http://studio.download.atmel.com/7.0.2389/as-installer-7.0.2389-full.exe
- Installer mit erhöhten Berechtigungen ausführen, danach:
 Checkbox Install latest version of product deaktivieren:

Atmel Studio 🗕 🗡
Atmel Studio 7.0
Newer version available
A newer version of the product is available. Select 'Install latest version' to download and install the latest available version.
Update information:
Microchip Studio
Renaming to Microchip Studio. Support for XC8 compiler for AVR devices.
Renaming to Microchip Studio. Support for XC8 compiler for AVR devices.
Install latest version of product
Next. Cancel
Next

3. • Checkbox I agree to the license terms and conditions aktivieren:



Next

4. • Checkboxen AVR 32-bit MCU und SMART ARM MCU deaktivieren:

Atmel Studio	
Atmel Studio 7.0	
Select Architecture	
AVR 8-bit MCU	
AVR 32-bit MCU	
SMART ARM MCU	
Back Next	Cancel

Next

5. • Checkbox Atmel Software Framework and Example Projects deaktivieren:

Attrier studio	- ^
Atmel Studio 7.0	
Select extensions	
Atmel Software Framework a Example Projects	nd
Back Next Cano	el

Next

6.	
	Atmel Studio _ ×
	Atmel Studio 7.0
	System validation Pending system reboot Installer Or WindowsUpdate Running Operating System Version Windows Update Running applications
	Refresh
	Back Next Cancel

■ Next

7.

mel Studio				-
Atmel S [.]	tudio 7	<i>'</i> .0		
important n	otes			
Device Header	ile Versions			
Some of the devi the Device Pack open the Compo	ice headers are Vlanager in the nents tab in th	updated. To insta Tools menu. To s e project properti	II different v et a version es.	ersions, use for a project,
	Back	Instal	1	Cancel

(Die unmittelbar darauffolgende Windows-Installationsabfrage mit Ja/Yes bestätigen.)

8. Alle folgenden Abfragen für die Gerätetreiberinstallationen mit *Installieren* bestätigen:



9. Checkbox Launch Atmel Studio 7.0 aktivieren

Atmel Studio		
Atmel Studio 7.0		
Installation complete Thank you for choosing Atmel Studio 7.0! Warning: Atmel LibUSB0 Driver (x64)		
☑ Launch Atmel Studio 7.0		
C	ose	

Close

Ende der Atmel Studio 7 Grundinstallation.